



Non-Contact Infrared Thermometer is used to measure human body temperature without physical touch. This temperature measurement gun is very safe, easy to use & gives fast and accurate response.

Just point the temperature measurement gun towards the object / body and click the trigger, it will measure the body temperature with a high degree of accuracy and display the same on the backlit large LCD screen panel at the rear of the temperature measurement gun.

Features

- High precision infrared sensor, stable and reliable performance
- Easy to operate
- 1s Quick measurement
- Safe and accurate measurements at a distance of 1 cm 5 cm
- Automatic Shutdown: During the wake-up mode, after 15 seconds of no action, the thermometer will go to sleep mode

ng Time: 1s Measuring Distance: 1g Bittel Intelligent Technology Co..L

- User selectable °C or °F (Centigrade & Fahrenheit degree)
- 2 IN 1 measurement modes: body / object temperature modes
- Automatically can save upto last 32 measurements
- Large LCD screen with backlit
- Fever alarm: High temperature benchmark setting that triggers an audible alarm



- Measuring Distance: 1 cm 5 cm
- Measuring Range: 32.5°C ~ 42.5°C (90.5°F ~ 108.5°F)
- Max Allowable Error: ±0.2°C (32.5°C ~ 42.5°C)
- Display Resolution: 0.1°C
- Operating Environment: 16°C ~ 38°C Humidity ≦85%
- Dimension: 149 mm x 95 mm x 43 mm
- Weight : 0.23 kg
- Storage Environment:-20°C ~ +55°C Humidity: ≦93%
- Power Supply: DC.3V (2pcs of AAA Batteries)
- Indicator:

1) It will show ERR if the operating temperature is lower than 16°C or higher than 38°C

2) It will show Li if the body temperature is lower than
32.5°C±0.2°C and will show Hi if it's higher than 42.5°C
±0.2°C

3) Low Battery Indicator

- Automatic shutdown time: 15 seconds
- Model No.: BITEWJ-02

Sales Enquiry: 011-4288 5508 Service Toll Free No: 1800 203 0131 www.progilitytech.com

Corporate Head Office: : Unit No. 1001, 10 Floor, Lodha Supremus, Wing - E, I Think Techno Campus, Kanjurmarg (East), Mumbai - 400 042, Maharashtra, India. Tel.: +91-22-4154 7000, Fax: +91-22-4154 7222, Email us - india@progilitytech.com

Our Reach

Ahmedabad I Aurangabad I Bengaluru I Bhopal I Bhubaneswar I Chandigarh I Chennai I Cochin I Coimbatore I Dehradun I Delhi I Goa I Gurgaon I Guwahati I Hyderabad I Jaipur I Jammu I Kolkata I Kota I Lucknow I Madurai I Mumbai I Nagpur I Patna I Pune I Raipur I Ranchi I Vadodara I Vijayawada I Visakhapatnam I Trichy